

SINGLE-PHASE, TRANSFORMERLESS BATTERY INVERTER WITH A DUAL MPPT SYSTEM

3TL M / 6TL M

The INGECON® SUN STORAGE 1Play TL M hybrid inverter makes it possible to combine photovoltaic generation and energy storage with no need for any additional PV inverters.

Dual MPPT system

This inverter features a dual maximum power point tracking (MPPT) system, that allows it to draw the maximum power from the PV array, including roof-mounted installations with different orientations or with partial shading.

EMS Inside

The inverter is equipped as standard with an energy management system (EMS). The EMS permits more advanced functionalities, such as

self-consumption. Thanks to the built-in EMS, the installation can be monitored at all times via a PC or mobile phone with the free INGECON® SUN Monitor application, available at Play Store and App Store.

Start-up and monitoring

Fast and easy start-up and display of data and graphics through the integrated user interface. Furthermore, users can easily upgrade the inverter firmware from the application, through a PC, tablet or mobile.

5 year warranty, extendible up to 25 years

PROTECTIONS

- AC overvoltages.
- Insulation faults.
- Short-circuits and overloads at the output.
- DC breaker for the PV array.
- Anti-islanding with automatic disconnection.

FEATURES

- Dual MPPT system.
- RS-485 communication for the wattmeter.
- Wi-Fi and Ethernet communication.
- CAN Bus 2.0 communication for the BMS (Battery Management System).
- 2 configurable digital inputs.
- 2 configurable potential free outputs.
- Pre-charging system at the battery input.
- Relay for the neutral to earth connection for critical loads in type TT installations.
- Rapid start-up and view of the installation thanks to the INGECON® SUN Monitor user interface.
- Possibility of operating just from the PV array and of adding the storage system at a later date.
- Suitable for indoor and outdoor installations (IP65).
- Back-up functionality available for self-consumption installations.
- DRM0 included (for the Australian market).



PV+battery hybrid systems, stand-alone and grid-connected

OPERATING MODES:

GRID CONNECTED MODES

- Self-consumption Mode

This operating mode is directed at grid connection systems with renewable energy sources, in order to minimise grid consumption. If the energy generated is greater than demand, then any surplus energy could either be used to charge the batteries or to be injected into the grid. In addition, it features a back-up functionality so that, in the event of a grid outage, the inverter can power the critical loads from the batteries and PV panels.

- UPS mode


This operating mode has been designed for systems where grid outages are long and frequent, meaning that a back-up power source is required. In order to guarantee a power source, the inverter maintains the batteries charged. During a grid outage, the inverter generates an AC network and the energy stored in the batteries is used to power the critical loads. Its rapid response time means that the grid outage is insignificant for most loads.

STAND-ALONE MODE


The INGECON® SUN STORAGE 1Play TL M inverter generates a stand-alone AC grid and acts as a grid manager, guaranteeing the correct balance between PV generation, consumption and the storage system.

It is equipped with a relay for the neutral to earth connection of the system loads in order to create a TT stand-alone network. Moreover, the inverter permits the connection of an auxiliary generator, which can be started-up through a potential-free output for charging the batteries.


WIRING DIAGRAM



Weight and dimensions (mm)



AC power in relation to battery voltage (with no PV power)



	3TL M	6TL M
Battery input (DC)		
Voltage range ⁽¹⁾	40 ~ 450 V	
Maximum charge / discharge current	66 A	
Type of battery	Lead-acid, ion-lithium (LG, BYD, Pylontech...) ⁽²⁾	
Communication with ion-lithium batteries	CAN Bus 2.0	
PV input (DC)		
PV array maximum power	11.5 kWp	
MPP voltage range	125 ~ 480 V	
Maximum input voltage ⁽³⁾	550 V	
Maximum input current (input 1 / input 2)	12 A / 12 A	
Number of MPPTs	2	
Number of inputs (input 1 / input 2)	1 / 1	
Grid input (AC)		
Rated voltage	230 V	
Voltage range	172 ~ 264 V	
Nominal Frequency	50 / 60 Hz	
Frequency range	40 ~ 70 Hz	
Network type	TT / TN	
Rated power	3 kW	6 kW
Max. temperature for rated power	40 °C	
Maximum current	13 Arms	26 Arms
Power factor	0 ~ 1	
Critical load output (AC)		
Power (25 °C) 30 min, 2 min, 3 s ⁽⁴⁾	3,500 / 3,900 / 5,080 W	6,400 / 6,900 / 7,900 W
Maximum current	13 Arms	26 Arms
Rated voltage ⁽⁵⁾	220 ~ 240 V	
Rated frequency ⁽⁵⁾	50 / 60 Hz	
Power factor	-0.8 ~ 1 ~ 0.8	
Back-up function response time	12 ms	
Features		
Maximum efficiency	95.5%	96%
Euroefficiency	95.1%	95.2%
Cooling system		
Cooling system	Forced ventilation	
Air flow	45 m³/h	
Consumption in stand-by mode	< 10 W	
Operating temperature	-20 ~ +65 °C	
Relative humidity (non-condensing)	4 ~ 100 %	
Protection class	IP65	
Maximum altitude	2,000 m	
Marking	CE	
EMC and safety regulations	EN 61000-6-1, EN 61000-6-2, EN 61000-6-3, EN 61000-6-4, EN 61000-3-11, EN 61000-3-12, EN 62109-1, EN62109-2, AS62040.1, FCC Part 15	
Grid connection standards	DIN V VDE V 0126-1-1, EN 50438, CEI 0-21, VDE-AR-N4105:2011-08, G59/3, G83/2, AS4777.2:2015, IEC 62116, IEC 61727, UNE 206007-1:2013, UNE 206006:2011, UNE 217001 IN:2015,NRS097-2-1, ABNT NBR 16149, ABNT NBR 16150, South African Grid code, P.O.12.2, G99, EN 50549-1	

Notes: ⁽¹⁾ The maximum power supplied by the battery shall be the battery voltage multiplied by the maximum discharge current ⁽²⁾ Consult the Ingeteam website for a list of compatible batteries ⁽³⁾ Never exceed. Consider the voltage increase of the panels 'Voc' at low temperatures ⁽⁴⁾ In stand-alone mode, these powers are only available if the power of the batteries added to the PV power reaches these values ⁽⁵⁾ Configurable voltage and frequency.



Ingeteam Power Technology, S.A.
Avda. Ciudad de la Innovación, 13
31621 Sarriguren (Navarra) - Spain
Tel.: +34 948 288 000 / Fax: +34 948 288 001
e-mail: solar.energy@ingeteam.com

Ingeteam S.r.l.
Via Emilia Ponente, 232
48014 Castel Bolognese (RA) - Italy
Tel.: +39 0546 651 490 / Fax: +39 054 665 5391
e-mail: italia.energy@ingeteam.com

Ingeteam SAS
La Naurouze B - 140 rue Carmin
31670 Labège - France
Tel: +33 (0)5 61 25 00 00 / Fax: +33 (0)5 61 25 00 11
e-mail: france@ingeteam.com

Ingeteam INC.
3550 W. Canal St.
Milwaukee, WI 53208 - USA
Tel.: +1 (414) 934 4100 / +1 (855) 821 7190 / Fax: +1 414 342 0779
e-mail: solar.us@ingeteam.com

Ingeteam, a.s.
Technologická 371/1
70800 Ostrava - Pustkovec
Czech Republic
Tel.: +420 59 732 6800 / Fax: +420 59 732 6899
e-mail: czech@ingeteam.com

Ingeteam, S.A. de C.V.
Leibniz 13 des 1101, Col. Anzures
Delg. Miguel Hidalgo,
11590 - Mexico - CDMX
Tel +5255 6586 9930-31
e-mail: northamerica@ingeteam.com

Ingeteam Ltda.
Rua Estácio de Sá, 560
Jd. Santa Genebra
13080-010 Campinas/SP - Brazil
Tel.: +55 19 3037 3773
e-mail: brazil@ingeteam.com

Ingeteam Pty Ltd.
Unit 2 Alphen Square South
16th Road, Randjiespark
Midrand 1682 - South Africa
Tel.: +2711 314 3190 / Fax: +2711 314 2420
e-mail: southafrica@ingeteam.com

Ingeteam SpA
Los militares 5890, Torre A, oficina 401
7560742 - Las Condes
Santiago de Chile - Chile
Tel.: +56 2 29574531
e-mail: chile@ingeteam.com

Ingeteam Power Technology India Pvt. Ltd.
2nd Floor, 431
Udyog Vihar, Phase III
122016 Gurgaon (Haryana) - India
Tel.: +91 124 420 6491-5 / Fax: +91 124 420 6493
e-mail: india@ingeteam.com

Ingeteam Sp. z o.o.
Ul. Koszykowa 60/62 m 39
00-673 Warszawa - Poland
Tel.: +48 22 821 9930 / Fax: +48 22 821 9931
e-mail: polska@ingeteam.com

Ingeteam Australia Pty Ltd.
iAccelerate Centre, Building 239
Innovation Campus, Squires Way
North Wollongong, NSW 2500 - Australia
Tel.: +61 455 521 490
e-mail: australia@ingeteam.com

Ingeteam Panama S.A.
Av. Manuel Espinosa Batista, Ed. Torre Internacional
Business Center, Apto./Local 407 Urb.C45 Bella Vista
Bella Vista - Panama
Tel.: +50 761 329 467

Ingeteam Service S.R.L.
Bucuresti, Sector 2, Bulevardul
Dimitrie Pompeiu Nr 5-7
Cladirea Hermes Business Campus 1,
Birou 236, Etaj 2 - Romania
Tel.: +40 728 993 202

Ingeteam Philippines Inc.
Office 2, Unit 330, Milelong Bldg.
Amorsolo corner Rufin St.
1230 Makati
Gran Manila - Philippines
Tel.: +63 0917 677 6039

Ingeteam