SUBSTATION AUTOMATION

### Ingeteam

### **INGETEAM** SUBSTATION AUTOMATION



Ingeteam has supplied protection, control and automation solutions for electrical substations for more than 25 years. More than 6,000 installations with our technology have been performed for the energy transmission and distribution and renewable energy generation industries.

Ingeteam makes available to our clients a network of professionals, covering 4 continents to offer both service and assistance during each phase of their projects, from the initial project definition phase to the end of the useful life of the equipment.

#### Index

Electrical grid digitalization	2
Protection and control systems	4
Substation automation	6
HMI / substation monitoring	8
Engineering tools	10
Substation gateway	12
Protection and control	14
Process bus	22
Standards and certification	26
International presence	28

### ELECTRICAL GRID DIGITALIZATION

The electrical grid is facing important changes due to the increase in the demand for electricity and the need to reduce  $CO_2$  emissions to achieve a more sustainable energy model.

Energy transmission and distribution systems face the challenge of **guaranteeing the stability of the grid** under this new model based on distributed generation, primarily associated with the **integration of renewable energy plants**.

Fossil fuel-based energy systems are centralized and easy to predict; however, the production of new sources of energy takes place at various locations and is therefore discontinuous and subject to variability, making the process more complex.

Digitalization of the grid makes it possible to have accurate information available about grid parameters at any given time. Real-time control of the grid provides the operator with **essential and accurate information** to improve proactive decision-making based on optimal information, thereby generating systems that are more efficient and reliable.

Protection, control and automation systems are key elements that guarantee a **reliable, efficient and sustainable electrical grid**.



Ingeteam's range of products, solutions and services facilitate digitalization of the electrical grid at all levels, reducing conventional cabling requirements and generating settings that are **safer and more environmentally friendly**.

Our equipment and services combine **protection**, **control and measuring** functionalities with the **latest technology** required by advanced communication processes. This, in turn, enables data acquisition, analysis and sharing between systems with the **highest degree of reliability and security**.

The control solutions offered by Ingeteam enable acquisition and management of grid data and parameters to identify situations, detect potential risks and react appropriately, thereby prolonging the service life of grid components and resources.



More than **25 years of activity** in the electricity transmission and distribution sector attest to the high standard of availability, reliability and flexibility provided by Ingeteam solutions and ensure troublefree implementation of the customer's requirements.

The range of Ingeteam products includes position control equipment, protection relays, substation remote control systems and gateways, as well as substation SCADA equipment with its corresponding software tools.



### PROTECTION AND CONTROL SYSTEMS



Ingeteam offers control solutions based on the **IEC 61850 standard**, comprised by intelligent electronic devices (IEDs) that control each electrical position and supply the collected data to a **SCADA** system, enabling operations, programming, analysis and reporting of all substation data, both locally and remotely.

#### **Functions**

- · Local or remote control of any component
- · Synchronization of all the components in the system
- · Acquisition of statuses, events and alarms
- · Grid quality measurements and information
- · Protection programming and fault registration
- · Analysis and decision-making information
- · Data records and logs
- · User profile and password-based access control
- · Control of communications between system components
- · Automation of position and/or substation processes (logical sequences as per IEC 61131 standard)
- · Acquisition of switch maintenance parameters
- · System self-checks

#### Redundancy

With the aim of creating secure, reliable and highly available systems, Ingeteam products work with **various types** of redundancy, whether applied to power supplies, HMI or communications.

Ingeteam equipment is designed so the same hardware can be used to select various types of **PRP/HSR redundancy** protocols, that provide tolerance of communication network failures without losing network operability, as set forth in the **IEC 62439-3 standard**. This provides engineers with the necessary flexibility to choose the best communications architecture for their systems, according to their needs.



#### **Synchronization**

Ingeteam equipment is capable of handling either millisecond precision, achieved with NTP or SNTP time protocols, or the most demanding 1 µs protocols provided for by the IEEE 1588 PTPv2 protocol, required in the process bus.

#### Cybersecurity

The equipment and systems have been implemented taking into consideration international cybersecurity standards, such as **IEEE 1686-2013** (IEEE Standard for Intelligent Electronic Devices Cyber Security Capabilities), **IEC 62351** (Power systems management and associated information exchange - Data and communications security) and **IEC 62443-4** (Security for industrial automation and control systems).

Ingeteam systems use cryptographic techniques with a variety of algorithms and coding standards, such as **HTTPs** or **sFTP**. They are also equipped with other cybersecurity functions, such as role-based username/ password access, control of access ports and security event auditing.



Communication architecture example







PANTALLA

### HMI/SUBSTATION MONITORING

P.R/TRI

INGESYS<sup>™</sup> IT is a **modular architecture software** consisting of all the modules necessary to implement Supervisory Control and Data Acquisition (**SCADA**), enabling efficient and intuitive information management.

INGESYS<sup>™</sup> IT is based on a modular, flexible structure capable of adapting to the customer's needs and **future market and technological developments**.

#### **Available modules**

- · Operating panels display
- Data and log management
- · Alarms and events management
- · Reports
- · Data analysis
- · Alarm notification
- · Website access
- · Access control and user profiles
- · Acquisition of switch maintenance parameters
- · System self-checks



Substation single-line diagram



Position control screen



### Real time control and data acquisition

Functio	<ul> <li>Graphical representation of data and measurements</li> <li>HTML5-based web operation panels with JavaScript support, compatible with the latest browsers</li> <li>Local substation control</li> <li>Presentation, management, acknowledgment, and storage of substation alarms and events</li> <li>Alarms are organized into areas depending on the level of severity</li> <li>Alarm notification via email or SMS, based on shift calendar and severity rules</li> <li>Management of communications with all the position control units via an IEC 61850 client for controlling, operating, configuring and signaling all the positions in the substation</li> <li>Exporting of alarms and events logs to text files</li> <li>Management of user access levels based on profiles, with restricted controls, access configurations, etc.</li> <li>Store and display of historical metering data logging</li> <li>Periodic Excel reports based on historical data</li> </ul>
Substation's dynam mimic diagram	
Communicatio	<ul> <li>SNMP for managing the communications network, substation unit alarms integrated into the panels, and system alarms</li> <li>High availability thanks to redundant communication mechanisms and to the node's redundancy</li> <li>SNTP synchronization</li> <li>Communication with different VLANs via IEEE 802.1Q</li> </ul>
Cybersecur	<ul> <li>User account management (roles and user levels) under IEC 61351 and IEEE 1686 standards</li> <li>Syslog remote log concentration service</li> <li>Centralized user accounts using LDAP authentication</li> <li>Firewall management</li> </ul>
Protoco	<ul> <li>IEC 61850 (client / server)</li> <li>IEC 60870-5-101 (master / slave)</li> <li>IEC 60870-5-103 (master / slave)</li> <li>IEC 60870-5-104 (master / slave)</li> <li>DNP3 TCP/IP and serial DNP3 (master / slave)</li> <li>PROCOME (master)</li> <li>MODBUS TCP/IP and MODBUS RTU (master / slave)</li> <li>OPC DA (client / server) and OPC-XML-DA (client / server)</li> <li>OPC UA (client / server)</li> </ul>



Panel editor



Communication status



### ENGINEERING TOOLS

Ingeteam provides its INGESYS<sup>™</sup> eFS software for the **configuration and operation** of an automated substation as per the **IEC 61850 standard**, thereby reducing costs and time in both the engineering and operation stages.

INGESYS<sup>™</sup> eFS consists of several software packages that facilitate engineering tasks on substation automation systems.

#### **Requirements covered**

- · Logic programming under IEC 61131-3 standard
- · Design of architectures and electrical diagrams
- Definition of operating philosophies
- Transfer of information and configurations
- Integration of third-party communication protocols
- Standard-based configuration files
- Protection functions
- Control functions
- Remote control functions
- Measurements



M () Section Magnet & Pattern	A RealDoke V SenterDoke A Selegione / 2 🖞 🕸 🔟 🖉 🔳		
D MENT DISKS NO. 01	2 · Providences   Publicences	* 10	
D C mar with	X - Norman - Norman		
- Convertigention	Description Description Description		
0 California	# UR + EC Place (M) UC - 1/ (+ Setting(s) - 50		
0 Calificat Intel Potector	N UN + DIC Phase (NI) US - N/ 14 Semanle)		
0-C Overcent	Bullel · 10	Ingeteam	Transmission 4. Distributions
D- DC Page	W Like - YOC Ground (NON) com 1 - 161/ 18 Gammagin)	-	I CONSTRUCTION OF CONSTRUCTION
- 0 04 1 2023	Bullet - 198 Genetic free - 199	Ene Bank Mantaon Bah	
D C TOCHARD	Bart solar (3) - E4 Generity Guide Type - AVII Asmal	😰 🕨 Time Signalis 🔜 R. M. S. 🚳 Vector 🗮 Measures 📓 Namonics 📰 😒	
D G DC No.44	Tere fol - 6.2 Genetic Ansature Res (mc) - 880	2 Mar 000000.4u	* X
6) - Cal 200, Service Ne	Topa cotol - todicadavi Bolina Inst - undradavi	File Name: EADICLO3VOxelo:_interestration/+1A_VR+40/0000003.r/g P65523 - UCL1 - PL300 - EH3022/M,05523 Start Date : 03/02/2010 10/02/00 719	707
to California (California)		Current Curser Date: COLECCIO LOGICE 7/2 Primery	
0 decire Manufal	Searchy . WE		•
Gi ca Droctanal 	III (8 + 700 Ground (2018) (mill 3 - 96) (18 Setting(2) Status	Statt:03/02/2010 10:02:00.719 TRIGGER 93/02/2010 10:02:00.028	
	W UR + TOC Decent (2019) Line 3 - 30/ 18 Setting(2)	- PRODUCT OF COMPANY	
D CL URINE D CL Prisoner	Buelled 1 50	V	
D 42 Paser Parletike	III (IR + 374 (second/2006) (15 - 1/ 34 (setting(s) - 1/ 34)		
- Coend Top	1 18 - 114 (second/208) 1/2 - 1/ 14 tuding(s)	187 research (Ha)	
in Calibration Fallone	Reini 1, 10		
E La Antonetere	6 (8 - 100 second(108) (0 - 6/ 54 telling(s) Reduct	Instant: 0 RMS: 0	
D-Ca UCA.ete-Configuration	With 1 Yes have devend (1991) 01 - 107 10 failing(a)		
H Ca 0020 Carlignation	Build : NO		
Endvanation Settings	10 101 - 101 Sens. ground(3000) 12 - 90/ 18 Setting(x)	-0.625 198.375	366,375 566,375
D La Spention	C 10 - 107 Same annual School up - 107 16 Samerica	0.06	
Van Spervice Iver Tenperature Spe	Decid - NO		
In Californian	G (A - 201 Serie ground(SMR) 45 - 87 51 Setting(c)		<sup>2</sup> to error er weidenen <sup>4</sup> ist i fligt <sup>2</sup> sin trock of her the alternative and
Passys Hearts Cadepapty configuration	E of a life face, another that is a factorized		
D-C2 Ant Multis	Nullei · · · · · · · · · · · · · · · · · · ·	nws: 0.0365	
*	W (W - 100 Serv. ground(1004) US - 6r 14 Setting(s)		la handa fandar (sere - Astro fetre -
Mara Setings	Nation	a start sec	** 8 Perfect MR31 Constants # Industral 2 Second control (
erdő 🛔 narapa 🛛 🄞 Malas_1022013,a	war can wooderconceptioneer terred	Envir	a constant a region of a document of the
			Fill a second se
		A CONTRACT OF A CO	
Durate at!	on adjustment screen		
Protectle	on adjustment screen	4 4 2 0,0014 4 2 0 0 0 14 4 0 0 0 0 0 0 0 0 0 0 0 0 0 0	
1 100000	on aajaoanone oor oon		
		benet: 8000	
		Turning of such and constructions of a set of a left of the desired	THE NO DI DI
		in 68	
		COMTRADE file viewer	28
			CTU N
			t tr the second se
			1888
		7. 8. 9. 1	K K R A A A A A A A A A A A A A A A A A

Logics editor

## System setup, analysis and maintenance software

iedFactory IED configuration	<ul> <li>IED graphics tool</li> <li>Modelling based on drag and drop actions</li> <li>Internal storage of all the IEDs modelled</li> <li>Dictionary with the definitions included in the standard to make understanding the models easier</li> <li>Creation and modification of datasets and control blocks</li> <li>Quick assignment of initial values and descriptions</li> <li>Graphical display of the information model in the form of a tree or data list with powerful filtering functions</li> <li>Import and export of ICD files</li> </ul>
substationFactory Substation/system configuration	<ul> <li>Instantiation of the substation's IEDs using the library defined in the iedFactory</li> <li>IEC 61850 substation graphics engineering tool</li> <li>Network topology and communication parameter configuration</li> <li>Dataset and control block editing: report control block, GOOSE control block, etc.</li> <li>Graphical display of the information model in the form of a tree or data list</li> <li>Generation of standard configuration files (CID, SCD files)</li> <li>Automatic documentation</li> <li>Setpoint description configuration</li> </ul>
operationFactory IEC 61850 client emulation	<ul> <li>Application configuration based on the following: CID files, IED database in the substationFactory tool or IEC 61850 self-descriptive services</li> <li>Option to store the information displayed in files compatible with Excel</li> <li>Powerful report monitoring mechanisms</li> <li>GOOSE message monitoring</li> <li>Log management</li> <li>MMS file browser</li> </ul>
emulationFactory IEC 61850 server emulation	<ul> <li>Emulates the behavior of a real device</li> <li>Application configuration based on the following: CID files or IED database in the substationFactory tool</li> <li>GOOSE generation</li> <li>Log server</li> <li>Graphical display of the information sent to clients</li> <li>Data exchange sequence and configurable event generation</li> <li>Generation of dynamic IP address</li> </ul>
gooseScan GOOSE message analyzer	<ul> <li>Configuration of the application based on: SCL files (CID / SCD)</li> <li>Multi-window display of the status of each GOOSE</li> <li>Identification of GOOSE refreshed and expired</li> <li>Recognition of updated GOOSE for quick identification</li> </ul>
mergeFactory SCL files comparison tool	<ul> <li>Navigation in the IEC 60850-6 directory tree</li> <li>Connection between both trees</li> <li>Summary presentation of the differences</li> <li>Comparison of standard sections: communications, substation, IED and Data Type Templates</li> <li>Comparison of SAddr initialization, settings, DataSet and control block, descriptions, etc.</li> <li>Comparison of private sections</li> </ul>
pacFactory Configuring and managing Ingeteam IEDs	<ul> <li>Relay setting tool</li> <li>CID file generation</li> <li>Configuration of communication network parameters: IP address, mask, etc.</li> <li>IEC 61850 protocol configuration: datasets, report control blocks, GOOSE messages</li> <li>CID file transfer via sFTP to the device</li> </ul>
recordCollector / recordNotifier Data concentrator for electrical protections	<ul> <li>Automatically collects events, fault and oscillographic files from the IEDs in COMTRADE format</li> <li>Storage in a local or remote repository</li> <li>File transfer via SFTP/FTP protocol</li> </ul>

### INGESAS CC3

### SUBSTATION GATEWAY



INGESAS<sup>™</sup> IC3 performs **gateway** and **remote** functions, allowing implementation of substation control logic and high-level **communication with SCADA**.

INGESAS<sup>™</sup> IC3 is high-performance modular equipment designed for substations that provides high availability and reliability thanks to its **redundant mechanisms**: redundant power supply, Hot-Hot / Hot-Standby systems, etc.

Its functionalities can also be implemented on an **industrial PC** for projects that require a specific hardware configuration due to concrete customer needs, such as additional communication ports, microprocessor, memory, etc.



INGESAS<sup>™</sup> IC3 includes a **web server** based on **HTML5** that enables viewing of fully configurable panels from any smartphone, tablet or PC, without needing to install any additional application.

INGESAS<sup>™</sup> IC3 includes **firewall** and **cybersecurity** functions that ensure correct use of the functionality.

### **Communications** concentrator

Enclosure	· 19" rack with 7 auxiliary slots
Communication ports	<ul> <li>4 Ethernet ports, 2 single and 2 switch with 2 outputs</li> <li>2 RS232/RS485 serial ports</li> <li>USB front port download/upload configuration</li> </ul>
LEDs	• 11 signalization + 5 status
Power supply (redundant optionally)	· 24, 48, 125, 220 Vdc (Vac available)
I/O card module	· 8DI/4DO
НМІ	Embedded HTML5 web server
IEC 61131-3 logics	· Yes
Redundancy (IEC 62439-3)	· PRP / HSR
Synchronization	SNTP / IEEE 1588 v2 / IRIG-B or telecontrol protocols
MMS and GOOSE messaging	· Yes, under IEC 61850-8-1 standard
Cybersecurity	<ul> <li>The device incorporates roles and privileges according to the IEC 62351 and IEEE 1686 standards</li> <li>LDAP authentication</li> <li>Firewall</li> <li>HTTPs, sFTP</li> <li>Syslog auditory log</li> </ul>
Protocols	<ul> <li>IEC 61850 (client / server)</li> <li>IEC 60870-5-101 (master / slave)</li> <li>IEC 60870-5-103 ( slave)</li> <li>IEC 60870-5-104 (master / slave)</li> <li>DNP3 TCP/IP and serial DNP3 (master / slave)</li> <li>PROCOME (master)</li> <li>MODBUS TCP/IP and MODBUS RTU (master / slave)</li> <li>OPC UA</li> </ul>

\* Wherever the application requires HW characteristics different from those offered by INGESAS™ IC3, there is the possibility of supplying the equipment embedded in an industrial PC that meets the corresponding requirements, with exactly the same functionality as any other INGESAS™ IC3.





### PROTECTION AND CONTROL



INGEPAC<sup>™</sup> EF is a range of high-performance intelligent electronic devices, developed on a **native IEC 61850 platform** for control and protection applications of electrical positions in high and medium-voltage substations.

Its processing capacity, high performance, multiple functionalities and modular hardware make it a **powerful and flexible solution** for the **automation** of any type of installation.

INGEPAC<sup>™</sup> EF is a totally programmable device, which includes data acquisition and reporting components and diagnosis and supervision components that **alert of any type of incident**, thereby facilitating fault detection and maintenance of the installation and the equipment itself and contributing to the **extension of the service life of the entire system**.



2 formats aluminum box: 19" 4U rack with 7 I/O slots 19" 5U  $\frac{1}{2}$  rack with 2 I/O slots



#### Communications

- · IEC 61850 certified by DNV in Ed.1 and Ed.2
- Redundancy, PRP and HSR under IEC 62439-3 standard, both in the station bus and the process bus
- Acquisition of sampled values as per IEC 61869-9 (NCIT) and IEC 61850-9-2LE (SAMU) standards
- Reception and transmission of MMS and GOOSE messages as per IEC 61850-8-1 standard
- Synchronization of IEEE 1588 v2 (PTP), SNTP, NTP or other protocols
- · Other protocols: DNP 3.0, Modbus, IEC 60870-5-103, IEC 60870-5-104

#### Cybersecurity and website access

- · Firewall functionality
- · Various levels of access via password
- Safe website access (HTTPs) and FTP (sFTP), from any device
- · Security logs
- · Disabling of communication ports
- · Verification of firmware integrity during upgrading

### Measurements and quality information

#### **Breaker supervision**

- · Excessive number of trips
- · kl2 breaker monitoring per pole
- · Closing and trip circuit monitoring
- · Breaker inactivity time monitoring



### PROTECTION AND CONTROL

	EF LD	EF ZT	EF TD
Features	Line differential	Distance protection	Transformer differential
Protection functions	87, 87LG, 87REF, 5th harmonic overexcitation, V/f, 21,POTT (21), POTT (67N/67Q), SOTF, 68LE, 68FF, 78, 67, 67N, 50/51, 50N/51N, 50G/51G, 67Q, 46FA, 37, 49, 59, 27, 59N, 47, 81M/m, 81R, 32, 25, 79, 74TC/CC, 50BF, Stub bus, Fault locator	21, POTT (21), POTT (67N/67Q), SOTF, 68ZC, 68OP, 68FF, 67, 67N, 50/51, 50N/51N, 50G/51G, 67Q, 46FA, 37, 49, 59, 27, 59N, 47, 81M/m, 81R, 32, 25, 79, 79 (81), 74TC/CC, 50BF, Stub bus, Fault locator	87T, 87REF, 5th harmonic overexcitation, V/f, 27, 59, 81, 81R, 50/51, 67N, 50G/51G, 46 (67Q), 49, 32, 50BF
Depending on the model	Single breaker or breaker and a half	Single breaker or breaker and a half	2 or 3 windings
Others	2 and 3 terminal lines	Up to 2 communication channels: FO, G703 or C37.94 (PUTT, POTT, DTT, etc.)	Valid for generators, motors or shunt reactors
Bay control	1 or 2 breakers	1 or 2 breakers	Yes
Analog channels	Up to 12 (144 samples/cycle)		
LEDs	19 programmable + 1 status		
Communication ports	Front: RJ45 + USB Rear: up to 2 Ethernet + 6 serial		
I/O card slots	7 or 2, depending on the enclosure (selectable modules)		
Modules	11DI/9DO, 32DI, 16DI/8DO, 16DI/16DO, 16DI/8AI, 8 DI/8DO, 11RTD/4AO		
Accuracy	Class 0.2		
IEC 61131-3 logics	Yes		
Redundancy (optional)	PRP/HSR (IEC 62439-3), link failover, switch mode		
Synchronization	SNTP / IEEE 1588 v2 / IRIG-B		
SV capturing	Yes, under IEC 61869-9 and IEC 61850-9-2LE (optional) standards		
MMS and GOOSE messaging	Yes, under IEC 61850-8-1 standard		
Cybersecurity	Firewall, HTTPs, sFTP, logs		
Protocols	IEC 61850, DNP3, IEC 60870-5-103, IEC 60870-5-104, Modbus, Procome		
Data acquisition	Event and fault register in non-volatile memory: measurements, quality, SOE, fault recorder, oscillography (COMTRADE files)		

EF VR	EF BF	EF CB	EF MD	EF CD	
Automatic voltage regulator	Breaker failure	Capacitor bank	Multifunction	Bay control	
90T	50BF, 67, 67N, 50/51, 50N/51N, 50G/51G, 67Q, 46FA, 49, 59, 27, 59N, 47, 81M/m, 81R, 68FF, 25, 79, 74TC/CC, Fault locator	67, 67N, 50/51, 50N/51N, 50Nu1/51Nu, 67Q, 46FA, 37, 59, 27, 59N, 47, 68FF, 79, 74TC/CC, 50BF	67, 67N, 67SN, 50/51, 50N/51N, 67Q, 46FA, 49, 59, 27, 59N, 47, 81M/m, 81R, 32, CLP, 50V/51V, 87N, 68FF, HCL, 25, 79, 79(81), 74TC/CC, 50BF, Fault locator, Intermittent faults	Bay control unit	
Single or parallel power transformers	Single breaker or breaker and a half	2 or 3 steps	67NA, 67NC, 50NS/51NS, 50G/51G, 37, 40, 78, 68ZC, SOTF, POTT (67/67Q),	0.2 measurement and synchronism	
Temperature supervision through RTDs inputs		Reactive, calendar or hours supervision			
Yes	1 or 2 breakers	Yes	Yes	Yes	
		Up to 12 (144 samples/cycle)			
	19 programmable + 1 status				
Front: RJ45 + USB Rear: up to 2 Ethernet + 6 serial					
	7 or 2, depending on the enclosure (selectable modules)				
11DI/9DO, 32DI, 16DI/8DO, 16DI/16DO, 16DI/8AI, 8 DI/8DO, 11RTD/4AO					
	Class 0.2				
	Yes				
PRP/HSR (IEC 62439-3), Link failover, switch mode					
SNTP / IEEE 1588 v2 / IRIG-B					
Yes, under IEC 61869-9 and IEC 61850-9-2LE (optional) standards					
Yes, under IEC 61850-8-1 standard					
Firewall, HTTPs, sFTP, logs					
IEC 61850, DNP3, IEC 60870-5-103, IEC 60870-5-104, Modbus, Procome					
	Event and fault register in non-volatile memory: measurements, quality, SOE, fault recorder, oscillography (COMTRADE files)				



### BUSBAR DIFFERENTIAL PROTECTION





The INGEPAC<sup>m</sup> EF bay units fulfill two functions in this solution. They are not only the **protection relays** for the corresponding bays, but they also act as **bay units** for busbar differential protection, offering an **cost-effective and efficient** solution with a significant **reduction in space and wiring**.

To ensure high availability and increase security, the units have **redundant PRP/HSR communications**, which guarantees that, in case of communication failure, there is no frame loss.

	EFx BD (central unit)	U 0.000 0 0 0 0 0.00 0 0 0 0 0.00 0 0 0 0 0.00 0 0 0 0 0.00 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0	
Protection functions	87, Checkzone, Differential alarm, Inrush, 86, Dead zone, Busbar breaker failure	67, 67N, 67SN, 50/51, 50N/51N, 67Q, 46FA, 49, 59, 27, 59N, 47, 81M/m, 81R, 32, CLP, 50V/51V, 87N, 68FF, HCL, 25, 79, 79(81), 74TC/CC, 50BF, Fault locator, Intermittent faults	
Additional features	Up to 5 zones/busbars and up to 24 bay units		
Bay control	Yes		
Analog channels	Depending on the number of bays: each bay unit has 12 analog channels with a 98 samples/cycle sampling frequency, as the IEC 61950-9-2 standard		
Leds	19 programmable LEDs and 1 status LED		
Front communication ports	RJ45 + USB		
Rear communication ports	Communication with bay units: 2 Ethernet x 1 Gb Communication with SAS: 2 Ethernet 10/100 Mbps + 3 serial ports	Communication with central unit: 2 Ethernet x 1 Gb Communication with SAS: 2 Ethernet 10/100 Mbps + 6 serial ports	
Slots (selectable modules)	8 o 3, depending on the enclosure	7 o 2, depending on the enclosure	
Modules	11ED/9SD, 32ED, 16ED/8SD, 16ED/16SD, 8 ED/8SD	11ED/9SD, 32ED, 16ED/8SD, 16ED/16SD, 16ED/8EA, 8 ED/8SD, 11RTD/4SA	
Accuracy	Class 0.2		
IEC 61131-3 logics	Ye	25	
Redundancy (optional)	PRP/HSR (IEC 62439-3), link failover, switch mode Available both for communication between central unit and bay units and for SAS communication		
Synchronization	IEEE 1588 v2 between the central unit and bay units SNTP / IEEE 1588 v2 / IRIG-B for SAS synchronization		
Cybersecurity	Firewall, HTTPs, sFTP, Logs		
Protocols (SAS)	IEC 61850, DNP3, IEC 60870-5-103, IEC 60870-5-104, Modbus, Procome		
Data acquisition	Event and fault register in non-volatile memory: measurements, quality, SOE, fault recorder, oscillography (COMTRADE files) SAS: Substation Automation and Control System		

### INGEPAC DAPT

QUIPO TRANSFERIDO I Puesta en marcha

E EELUEE

### PROTECTION AND CONTROL

The multifunction devices of the INGEPAC<sup>™</sup> DA PT product range offer a compact design on a native **IEC 61850** platform to protect and control positions of medium voltage lines or small motors.

INGEPAC<sup>™</sup> DA PT provides high user flexibility through its powerful logic programming capacity, local interface and communication ports that can **operate locally or remotely**, as well as its automatic functions.

INGEPAC<sup>™</sup> DA PT is equipped with **diagnostic and supervision** components, event logs, fault reports, measurement logs and oscillographic capabilities for complete incident analysis.



	DA PT1 DA PT6		
Features	Feeder protection relay Motor protection relay		
Protection functions	67, 67N, 67SN, 67NA/NC, 50/51, 50N/51N, 50SN/51SN, 67Q, 46FA, 59, 27, 59N, 47, 81M/m, 81R, CLP, HCL, HLT, 68FF, 79, 25, 74TC/CC, 50BF, 32, 78, Fault locator 67, 67N, 67SN, 67NA/NC, 50/51, 50N/51N, 50SN/51SN, 67Q, 46FA, 59, 27, 59N, 47, 81M/m, 81R, CLP, HCL, HLT, 68FF, 79, 25, 74TC/CC, 50BF, 32, 78, Fault locator 51LR, 37, 66, 48, 14		
Optional	Arc detection, up to 4 optic sensor inputs		
Bay control	Yes		
Analog channels	Up to 8 (144 samples/cycle)		
Power supply	24, 48, 125, 220 Vdc		
LEDs	24 programmable + 1 status		
Communication ports	Front: RJ45 + RS232/485 + USB / Rear: up to 2 Ethernet + 1 serial RS232/485		
I/O card slots	Up to 2 DI/DO/AI (selectable modules)		
Modules	15DI/8DO, 2 <mark>4DI/16</mark> DO, 13 DI, 8 AI		
Accuracy	Class 0.2		
IEC 61131-3 logics	Yes		
IEC 62439-3 redundancy	PRP / HSR		
Synchronization	SNTP / IEEE 1588 / IRIG-B		
MMS and GOOSE messaging	Yes, under IEC 61850-8-1 standard		
Cybersecurity	Firewall, HTTPs, sFTP, Logs		
Protocols	IEC 61850, DNP3, IEC 60870-5-101, IEC 60870-5-103, IEC 60870-5-104, Modbus		
Data acquisition	Event and fault register in non-volatile memory. COMTRADE files		



### Arc detection

INGEPAC<sup>™</sup> DA PT has **up to 4 inputs for INGEPAC<sup>™</sup> LSD optic sensors**. This enables detection of electrical arcs and provides **additional protection** to cells against these severe incidents, which endanger both the safety of the installations and the staff that maintains them. Ń



### PROCESS BUS

The process bus is a communications network based on the **IEC 68150-9-2 standard**, capable of digitalizing the information of the primary patio equipment (voltage transformers, current transformers, switches, etc.) to be transmitted via a **fiber optic network** to the protection, control and measurement IEDs.

Ingeteam offers a range of equipment that act as the interface between the primary switchgear and the substation's protection and control system.



INGEPAC<sup>™</sup> EF PB is the **merging unit** developed by Ingeteam that collects the analog signals from the measurement transformers, and transmits them through the process bus as **Sampled Values** (SV).

INGEPAC<sup>™</sup> EF PB is an IEC 61850 server that can also transmit and receive digital signals such as **GOOSE messages** as per the IEC 61850-8-1 standard, allowing easy, reliable and economic implementation of the process bus.

The merging units synchronize with the different IEDs through the IEEE 1588 v2 protocol, which provides an accuracy better than 1 microsecond, allowing the correct sampling of the analog measurements with the required precision.

Complementary to the merging units, INGEPAC<sup>™</sup> DA PTC product range acts as a **digital interface**, allowing the management of signals from switches, breakers or any other primary component, suitable for use in both the process and station buses.



GOOSE and IEEE 1588 v2 monitoring screen



INGEPAC<sup>™</sup> EF PB



Cabinet with INGEPAC<sup>™</sup> DA PTC

### INGEPAC EFPB

### PROCESS BUS



INGEPAC DAPTC

Fiber optic channeling of the process bus

Implementation of the process bus involves various economic, logistic and security benefits.

#### **Benefits**

- Time savings in substation engineering and installation
- Copper cabling is reduced in a high percentage due to the use of optical fiber
- Smoother expansion and modernization of an existing substation
- · Easier maintenance
- Reliable systems with multiple self-diagnosis and supervision systems
- Faster substation power-up
- $\cdot\,$  Smaller protection circuits, enabling smaller CTs
- Increased security: process bus significantly reduces the risk for a current circuit to remain open
- More sustainable substations



INGEPAC<sup>™</sup> EF is the range of IEDs with capacity to connect merging units or electronic transformers built to comply with **IEC 61850-9-2** or **IEC 61869-9** standards.

	EF PB	DA PTC
IEC 61850-9-2 sampled values	8 or 12, depending on the model	No
GOOSE	Yes, under IEC 61850-8-1 standard	
Enclosure	19" 3U rack, 19" 4U rack or 1/2 19" 5U rack	1/3 19" rack, 1/3 19" rack surface mount or 2/3 19" rack
I/O card slots	2, 3 or 6, depending on the format	2 or 4, depending on the format
Modules	11ED/9SD, 32ED, 16ED/8SD, 16ED/16SD, 16ED/8EA, 8ED/8SD	15ED/8SD, 24ED/16SD, 13ED, 8EA (mA/V)
Power supply	24, 48, 125, 220 Vdc	24, 48, 125, 220 Vdc
Redundant power supply	Optional	No
LEDs	11 programmable + 1 status	Up to 24 programmable + 1 status
Front communication ports	RJ45 + USB RJ45 + USB	
Rear communication ports	Up to 6 serial and 2 Ethernet	1 serial and 2 Ethernet
IEC 61131-3 logics	Yes	Yes
Communications	PRP / HSR optional	PRP / HSR optional
Synchronization	IEEE 1588, PPS, SNTP, IRIG-B	IEEE 1588, SNTP, IRIG-B
Web services	Web page and sFTP	
Event recorder	Yes	

### STANDARDS AND CERTIFICATION



#### Design

As part of its commitment to quality and customer satisfaction, Ingeteam applies these processes and conducts comprehensive tests on all the equipment it manufactures to ensure compliance with the highest quality standards and regulations.

Ingeteam equipment is certified by **independent external laboratories** in compliance with **international standards** for electric, climatic and mechanical testing, thereby ensuring optimal performance.

The equipment designed by Ingeteam complies with the following directives and standards:

- · Low Voltage Directive 2006/95/EC
- EMC Directive 2004/108/EC
- · IEC 60255-1
- · IEC 60255-26
- · IEC 60255-27

#### **Additional protection**

Optionally, the equipment can be provided with a cover that affords a **frontal IP54 or IP55 protection** grade, as established in the **IEC 60529 standard**, recommended for settings where dust or particles in suspension may be present.

The manufacturing process of the equipment contemplates the option of providing additional protection to withstand exposure to **hostile surroundings** or high humidity or temperature weather conditions, thereby improving and prolonging equipment service life and reliability.

The coatings used in this process meet the requirements of **RoHs 2002/95/EC** directive and the **UL QMJU2** certification.



#### Communications

All the equipment manufactured by Ingeteam are designed on a **native IEC 61850 platform** and have passed an external certification process performed by the **KEMA laboratory** that guarantees operation with other IEDs from other manufacturers that also comply with the standard.

In addition, Ingeteam is **ISO 27001** certified for **information security and privacy**, which guarantees the confidentiality and integrity of the data managed by the company.

### Quality

Ingeteam Power Technology, S. A. holds the ISO 9001 certification, which guarantees that it meets applicable legal and regulatory requirements and implements continuous improvement processes.

It also holds the **ISO 14001** certification, which specifies **environmental management** requirements and attests to Ingeteam's commitment to protection of the environment.



### INTERNATIONAL PRESENCE

# Ingeteam has a network of offices, factories, distributors and VARs to serve the customer closely



#### **CENTRAL OFFICE**

INGETEAM POWER TECHNOLOGY, S. A. Parque Tecnológico de Bizkaia, Edificio 110 48170 Zamudio, Bizkaia - Spain Tlf.: (+34) 944 039 600

#### **MEXICO OFFICE**

INGETEAM POWER TECHNOLOGY MÉXICO S. DE R. L. DE C. V. Av. Ejército Nacional Mexicano, 351 - Piso 6, Chapultepec Morales, Granada, Miguel Hidalgo, 11520 Ciudad de México, CDMX Tlf.: (+52) 55 6586 9930

#### **BRAZIL OFFICE**

INGETEAM LTDA. Rua Tenente Francisco Ferreira de Souza, 2145, Boqueirão, Curitiba, Paraná - Brasil CEP 81070-010 Tlf.: (+55) 41 3276-9841 / 9193-2042

#### **THAILAND OFFICE**

100/67 Vongvanij bldg. B, 22nd floor Rama IX Rd Huaykwang 10320 Bangkok - Thailand Tlf.: (+66) 224 61798

### powergridautomation@ingeteam.com



www.ingeteam.com